



AH-0218



AH-9719

AH-0218  
AH-9719

### Fire Alarm Bell & Indicating Lamp

#### AH-0218 Fire Alarm Bell 6"

- High efficiency low current consumption on 24VDC motorized bells.
- Terminals will accept 2.5mm cables.
- Simple installation via multi-fixing base plate for all types of location.
- Fitted with two series diodes for fault monitoring.
- Option of customized discs printed with company name and logo.
- 12VDC bells are also available.

#### AH-9719 Fire Indicating Lamp

- Uses white bulb (or low current LED) and installed inside the red lamp cover.
- When lit, it is clearly visible within 10 meters.

#### Specifications

Model	AH-0218
Dimensions	Ø6" (152mm) x 56mm(H)
Voltage	24V DC
Current	25mA
Sound Output	93dB @1M
Movement	Motor, Pinion and striker
Movement Features	DC Motor, acetal gear wheel, steel striker
Gong	Steel, secured with Phillips screw
Base Plate	Molded black polycarbonate
Material	Steel plate
Weight	About 850g

#### Specifications

Model	AH-9719
Dimensions	90mm(Dia.) x 70mm(H)
Consumption Current	24V DC 60mA / LED 20mA
Bulb	30V/2W bulb or LED
Lamp Cover	Fire-proof plastic
Lamp Base	Fire-proof plastic
Weight	About 70g

AH-0218

EN54



AH-9719

